

NOTES

1. EXTENT OF WORKS

THE ELECTRICAL SERVICES SUB-CONTRACT INCLUDES BUT IS NOT LIMITED TO THE FOLLOWING:

- SURVEY OF ALL EXISTING UNDERGROUND SERVICES IN THE VICINITY OF THE WORKS.
- SUPPLY AND INSTALLATION OF ALL COMPONENTS FORMING PART OF THE ELECTRICAL SERVICES.
- CO-ORDINATION.
- INSPECTIONS.
- TESTING AND COMMISSIONING.
- MAINTENANCE.
- UPDATE THE SCHOOLS EXISTING AS BUILT DRAWINGS.
- UPDATE THE SCHOOLS EXISTING MAINTENANCE MANUAL.
- CABLING, CABLE SUPPORT SYSTEMS AND ACCESS.
- POWER DISTRIBUTION.
- LIGHTING.
- COMMUNICATIONS CABLING.
- MODIFICATION, RELOCATION AND EXTENSION AS NECESSARY OF ALL EXISTING SERVICES THAT ARE IMPACTED BY THE WORKS OR REQUIRED TO BE EXTENDED BY THE WORKS.
- REMOVAL OF ALL EXISTING SERVICES MADE REDUNDANT BY THE WORKS.
- ANY TEMPORARY WORKS REQUIRED TO KEEP THE SCHOOL OPERATING DURING THE CONSTRUCTION PROCESS.
- ALL MINOR COMPONENTS AND INCIDENTAL WORKS NOT SPECIFICALLY REFERRED TO, HOWEVER NECESSARY TO COMPLETE THE ELECTRICAL SERVICES INSTALLATION SUCH THAT IT IS HANDED OVER COMPLETE, OPERATIONAL AND FIT FOR THE INTENDED USE.

SUPPLY ALL LABOUR, MATERIALS, EQUIPMENT, AND ALL OTHER ITEMS, WHETHER MENTIONED IN DETAIL OR NOT, REQUIRED FOR THE SATISFACTORY COMPLETION OF THE ELECTRICAL SERVICES INSTALLATION, LEAVING IN FULL WORKING ORDER TO THE SATISFACTION OF THE PROJECT MANAGER.

PRIOR TO COMMENCING WORK CONSULT THE SCHOOL MANAGEMENT FOR ANY HAZARDOUS MATERIAL AND OR ASBESTOS REGISTERS AS WELL AS UNDERTAKE A THOROUGH INSPECTION OF THE SITE TO IDENTIFY ANY POTENTIAL HAZARDOUS MATERIALS, ASBESTOS AND HEALTH OR SAFETY RISKS. ADVISE THE CONTRACTOR OF ANY POTENTIAL HAZARDOUS MATERIALS, ASBESTOS AND HEALTH OR SAFETY RISKS IF IDENTIFIED AND DO NOT COMMENCE WORK UNTIL AN APPROPRIATE MANAGEMENT PLAN HAS BEEN DEVELOPED AND AGREED TO BY ALL PARTIES

PRIOR TO COMMENCING WORK UNDERTAKE A DETAILED ACTIVE SURVEY OF ALL EXISTING UNDERGROUND SERVICES IN THE VICINITY OF THE WORKS. IDENTIFY ALL EXISTING UNDERGROUND SERVICES WITHIN THE SCOPE OF THE WORKS. THE SURVEY WILL NEED TO INCLUDE VACUUM EXCAVATION. PROVIDE A COPY OF THE SURVEY FOR APPROVAL INCLUDING ALL PITS AND CONDUITS DIMENSIONED OFF EXISTING BUILDINGS, THE CONTENTS OF THE CONDUITS INCLUDING THE CABLE TYPE SOURCE AND DESTINATION.

SUPPLY ALL LABOUR, MATERIALS, EQUIPMENT, AND ALL OTHER ITEMS, WHETHER MENTIONED IN DETAIL OR NOT, REQUIRED FOR THE SATISFACTORY COMPLETION OF THE ELECTRICAL SERVICES INSTALLATION, LEAVING IN FULL WORKING ORDER TO THE SATISFACTION OF THE PROJECT MANAGER.

ACCEPT FULL RESPONSIBILITY FOR LIASING, ARRANGING AND CO-ORDINATION OF ALL WORKS THAT HAVE AN EFFECT ON OR WILL BE AFFECTED BY THE ELECTRICAL SERVICES.

CONFIRM THE POSITION OF ALL OUTLETS ON SITE WITH THE SCHOOL PRIOR TO ROUGH-IN.

UPDATE THE SCHOOLS EXISTING AS BUILT DOCUMENTS AND MAINTENANCE MANUAL TO INCLUDE THE NEW WORKS.

PROVIDE ALL FITTINGS MOUNTED WITHIN THE PERFORATED SECTIONS OF THE PLASTER BOARD CEILING WITH AN EXTENDED MOUNTING TRIM THE SAME COLOUR AS THE FITTING. PROVIDE DETAILS OF THE MOUNTING TRIM TO THE ARCHITECT FOR APPROVAL.

ANY INTERRUPTION TO ANY ELECTRICAL SERVICES OUTSIDE OF THE AREA OF WORKS MUST BE RESTRICTED TO OUTSIDE OF THE SCHOOLS OPERATING HOURS AND MUST BE ADVISED TO THE SCHOOL IN WRITING TWO WEEKS PRIOR AND LIMITED TO FOUR HOURS.

2. WORKMANSHIP

ENSURE THAT THE ELECTRICAL WORK IS PERFORMED BY THE HOLDER OF A CURRENT ELECTRICAL SUB CONTRACTOR LICENSE AND THE SERVICES COVERED BY THE ACMA IS PERFORMED BY THE HOLDER OF THE APPROPRIATE CURRENT ACMA LICENSE. ENSURE THE INSTALLATION AND ALL COMPONENTS, FIXTURES, FITTINGS, OUTLETS AND CABLES ARE SUPPLIED AND INSTALLED TO A HIGH STANDARD THROUGHOUT, AND INSTALLED IN A NEAT AND TRADESMAN LIKE MANNER, TO THE CURRENT INDUSTRY STANDARDS. ENSURE ALL MATERIALS AND COMPONENTS OF A SIMILAR TYPE ARE OF THE SAME MANUFACTURER AND INSTALLED IN A UNIFORM MANNER.

IT IS THE ELECTRICAL SUB CONTRACTOR'S RESPONSIBILITY TO ENSURE THAT THE INSTALLATION IS FIT FOR PURPOSE AND IS PROVIDED AS A COMPLETE WORKING INSTALLATION. IT IS THE ELECTRICAL SUB CONTRACTOR'S RESPONSIBILITY TO PROVIDE ALL COMPONENTS, FITTINGS, FIXTURES, SYSTEMS, PROGRAMMING ETC IRRESPECTIVE OF THE LEVEL DETAILED IN THE DOCUMENTS SUCH THAT THE INSTALLATION IS PROVIDED AS A COMPLETE WORKING INSTALLATION.

CONCEAL ALL WIRING AND CONDUITS. EXPOSED CABLING OR CONDUITS ARE GENERALLY NOT ACCEPTABLE. IT IS NOTED THAT CHASING AND REINSTATEMENT WILL BE REQUIRED. ENSURE ALL COMPONENTS, EQUIPMENT AND MATERIALS SUPPLIED ARE NEW, UNUSED, DESIGNED AND SELECTED TO ENSURE SATISFACTORY OPERATION UNDER VARYING ATMOSPHERIC, CLIMATIC, HUMID TROPICAL CONDITIONS WITHOUT DISTORTION AND DETEIORATION IN ANY PART AFFECTING EFFICIENCY AND RELIABILITY OF THE SYSTEMS. DESIGN AND SELECT ALL EQUIPMENT TO PROVIDE THE NECESSARY SAFETY TO HUMAN LIFE AND PROPERTY DURING OPERATION AND MAINTENANCE WITH PARTICULAR ATTENTION GIVEN TO ELECTRICAL SAFETY AND SEGREGATION PRECAUTIONS.

CHECK THE FINISHED PAINTWORK AROUND THE AREA OF EACH INSTALLATION AND TOUCH UP ALL DAMAGED PARTS AND FINISHES AFTER THE INSTALLATION OF THE ELECTRICAL SERVICES.

ALL WORKS ARE TO BE CARRIED OUT IN ACCORDANCE WITH THE BUILDER'S PROGRAM. ENSURE ALL FINAL LOCATIONS OF OUTLETS AND FITTINGS ARE CO-ORDINATED ONSITE WITH THE ARCHITECT AND ALL OTHER SERVICES, TO THE APPROVAL OF THE PROJECT MANAGER. ALLOW TO CO-ORDINATE THE FINAL LOCATION OF ALL EQUIPMENT, FITTINGS, & OUTLETS, SUCH THAT THEY ARE INSTALLED IN ACCORDANCE WITH THE AS3000 RESTRICTED ZONES, AND ARE NOT COVERED INAPPROPRIATELY.

ENSURE THAT ALL METAL SURFACES ARE SUITABLY PROTECTED AGAINST CORROSION, AND THAT ALL PLASTIC MATERIALS ARE UV STABILISED.

PROVIDE ALL MATERIALS AS NEW, AND OF THE HIGHEST CLASS AVAILABLE FOR THEIR RESPECTIVE TYPES. ENSURE ALL ASPECTS OF THE WORK ARE OF A HIGH STANDARD THROUGHOUT, AND INSTALLED IN A NEAT AND TRADESMAN LIKE MANNER, TO THE CURRENT INDUSTRY STANDARDS.

IRRESPECTIVE OF INFORMATION CONTAINED IN THE ELECTRICAL SERVICES DOCUMENTS OR IN INSTRUCTIONS, IT IS THE ELECTRICAL SUB CONTRACTOR'S RESPONSIBILITY TO ENSURE ALL ELECTRICAL SERVICES WORKS ARE INSTALLED IN ACCORDANCE WITH THE REQUIREMENTS OF THE FOLLOWING. REFER ANY DISCREPANCIES BETWEEN THE REQUIREMENTS OF THE FOLLOWING AND/OR THE ELECTRICAL SERVICES DOCUMENTS AND INSTRUCTIONS TO THE ARCHITECT FOR CLARIFICATION PRIOR TO THE PLACING OF ORDERS, FABRICATION OR INSTALLATION OF THE ITEMS/METHODS IN DISCREPANCY.

- NCC BUILDING CODE OF AUSTRALIA.
- ELECTRICITY ACT.
- ELECTRICAL SAFETY ACT.
- ENERGEX REQUIREMENTS.
- THE QUEENSLAND ELECTRICITY CONNECTION MANUAL V4 (QECM) AND THE NATIONAL ELECTRICITY METERING STANDARDS (NEM).
- AS/NZS3000.
- AS3008.
- LOCAL BRIGADE.
- WORKPLACE HEALTH AND SAFETY ACT.
- TELECOMMUNICATIONS ACT.
- ACMA REQUIREMENTS.

NOTES

3. AUTHORITIES

ENSURE ALL OF THE ELECTRICAL SERVICES COMPLY WITH THE REQUIREMENTS OF ALL REGULATORY AUTHORITIES HAVING JURISDICTION OVER THE SITE INCLUDING BUT NOT LIMITED TO THE FOLLOWING:

- ACMA.
- LOCAL COUNCIL.
- ENERGEX.
- STATE GOVERNMENT DEPARTMENT OF ENVIRONMENT AND HERITAGE.
- QLD GOVERNMENT, DIVISION OF WORKPLACE, HEALTH AND SAFETY.
- QLD FIRE AND EMERGENCY SERVICES.

4. CABLES

UNLESS OTHERWISE SPECIFIED, INSTALL AND TERMINATE CABLES IN ACCORDANCE WITH THE MANUFACTURERS' RECOMMENDATIONS. DETERMINE THE FINAL ROUTES TO SUIT THE BUILDING STRUCTURE AND SITE CONDITIONS. UNLESS NOTED OTHERWISE, PROVIDE ALL 240 VOLT POWER AND LIGHTING WIRING AS 2.5mm² TWIN & EARTH STRANDED COPPER CONDUCTORS, PVC INSULATED 0.6/1kV V75 GRADE TO AS3174, PROTECTED BY A 20 AMP CIRCUIT BREAKER. ALL CONDUIT AND FITTINGS TO BE RIGID UPVC TO AS2053, UNLESS NOTED OTHERWISE.

5. POWER DISTRIBUTION

IN ADDITION TO THE WORKS ASSOCIATED WITH THE BUILDINGS THE POWER DISTRIBUTION COMPONENT OF THE ELECTRICAL SERVICES SUB-CONTRACT INCLUDES REPLACING THE EXISTING WESTERN ENERGEX POLE MOUNT TRANSFORMER AND ASSOCIATED MSB WITH A NEW ENERGEX PADMOUNT SUBSTATION AND MSB.

ENSURE THE NEW ENERGEX SUPPLY, MSB AND MDB ARE COMPLETE AT LEAST TWO MONTHS PRIOR TO PRACTICAL COMPLETION FOR COMMISSIONING. ARRANGE WITH THE BUILDER FOR THE SUBSTATION STRUCTURE TO BE COMPLETE AT LEAST SIX WEEKS PRIOR TO THE INSTALLATION OF THE ENERGEX TRANSFORMER. CUT OVER THE POWER SUPPLY FROM THE EXISTING MSB AND POLE MOUNT TRANSFORMER TO THE NEW PADMOUNT SUBSTATION DURING SCHOOL HOLIDAYS.

CONFIRM A MINIMUM 25M SEPARATION BETWEEN THE POWER INSTALLATION ZONE A AND THE POWER INSTALLATION ZONE B IS MAINTAINED WITH NO MAINS POWER ENTERING THE SEPARATION AREA BETWEEN THE TWO ZONES. SUBMIT TO ENERGEX FOR APPROVAL A COMPUTER-AIDED DESIGN (CAD) DIAGRAM WHICH IDENTIFIES ZONES ON THE LOT FOR THE TWO SEPARATE ELECTRICAL INSTALLATIONS WHICH INCLUDES THE FOLLOWING:

- THE LOT NUMBER AND;
- THE NETWORK SUPPLY POINTS WITH NMIs SHOWN;
- BOTH GEOGRAPHICAL AND ELECTRICAL DEMONSTRATION OF THE EXTENT OF THE ZONES;
- THE ZONES SHALL BE NAMED A AND B.
- THE ZONE BOUNDARIES SHOULD BE AS SIMPLE AS POSSIBLE, USING OBVIOUS BOUNDARIES SUCH AS ROADS, FENCES OR WATERWAYS.
- ALL SWITCHBOARDS AS WELL AS ANY EQUIPMENT REMOTE OF A BUILDING (SUCH AS LIGHTING, GATES ETC.) SHALL BE LABELLED ON THE DIAGRAM WITH A UNIQUE IDENTIFIER TO THE PREMISES, WITH THE ZONE LETTER AS PART OF THE NAMING.
- THE ADDRESS OF EACH ENERGEX SUPPLY.

PROVIDE A LAMINATED COPY OF THE EXISTING ENERGEX DUAL POINTS OF SUPPLY DISPENSATION AND THE ABOVE PLAN IN THE NEW MSB AND THE EXISTING EASTERN BOUNDARY MSB-E ADJACENT GEMVALE ROAD. AN ELECTRONIC COPY OF THE DISPENSATION WILL BE PROVIDED BY THE ELECTRICAL DESIGN GROUP WHEN REQUESTED BY EMAIL.

RECOVER THE EXISTING MSB AND RETURN IT TO THE COLLEGE UNLOADED IN A REMOTE POSITION ON THE REEDY CREEK SITE AS DIRECTED BY THE COLLEGE.

ARRANGE WITH ENERGEX TO HAVE THE NEW PADMOUNT SUBSTATION INSTALLED. PROVIDE AN UNDERGROUND CONSUMERS MAIN FROM THE SUBSTATION TO A NEW MAIN SWITCHBOARD.

THE EXISTING WESTERN MSB-W IS TO BE REMOVED. THE EXISTING ENERGEX SUPPLIES TO THE RESIDENCES AND THE BUS DEPOT ARE TO BE REMOVED.

A NEW MAIN DISTRIBUTION BOARD MDB IS TO BE PROVIDED AND SUPPLIED FROM THE NEW MSB VIA AN EXTENSION OF THE EXISTING UNDERGROUND CONDUITS. THE EXISTING SUBMAINS THAT SUPPLY DB-K, DB-C1, DB-NS AND DB-S (SERVER) ARE TO BE JOINED IN THE PIT UNDER THE EXISTING MSB WITH WATERPROOF JOINS AND EXTENDED TO THE MDB. THE EXISTING SUBMAINS TO DB-G AND DB-LP ARE TO BE REMOVED AND REPLACED WITH NEW SUBMAINS SUPPLIED FROM THE NEW MDB.

NEW DISTRIBUTION BOARDS DB-TS, DB-MS AND DB-DS ARE TO BE PROVIDED AND SUPPLIED WITH NEW SUBMAINS FROM THE NEW MDB. NEW SUBMAINS ARE TO BE PROVIDED FROM THE NEW MDB TO MSSB-1 AND MSSB-2.

THE POWER DISTRIBUTION COMPONENT OF THE ELECTRICAL SERVICES SUB-CONTRACT INCLUDES THOUGH IS NOT LIMITED TO THE FOLLOWING EXTENT OF WORK:

- ENERGEX PADMOUNT SUBSTATION INCLUDING ALL CIVIL WORKS REQUIRED BY ENERGEX.
- ARRANGE THE ENERGEX SUPPLY CONNECTION AND METERING.
- UNDERGROUND CONSUMERS MAINS FROM THE ENERGEX PADMOUNT SUBSTATION TO THE MSB.
- MAIN SWITCHBOARD (MSB).
- UNDERGROUND SUBMAIN FROM THE MSB TO DB-G.
- DISTRIBUTION BOARD DB-G.
- SUBMAIN FROM THE DB-G PROTECTED BY A MCCB TO THE MSSB.
- EARTHING.
- CIRCUITS.
- ISOLATORS AND OUTLETS.
- SWITCH PANELS.
- INSTALLATION OF THE HAND DRYERS.
- CABLE ACCESS WAYS.
- CABLE ACCESS HAT SECTION.
- TESTING AND COMMISSIONING.
- REMOVAL OF THE EXISTING ENERGEX AERIAL SERVICE, POLE MOUNT TRANSFORMER, WESTERN CONSUMERS MAINS AND WESTERN MAIN SWITCHBOARD MSB-W.
- REMOVAL OF THE EXISTING ENERGEX LV AERIAL SERVICE TO THE BUILDING ON THE SOUTHERN BOUNDARY INCLUDING THE MEN, AND METERING.
- REMOVAL OF ALL EXISTING SERVICES MADE REDUNDANT BY THE WORKS.
- THERMOSCAN ALL OF THE SWITCHBOARDS SUPPLIED OR MODIFIED AS PART OF THE WORKS WITHIN THE FIRST WEEK SCHOOL HAS COMMENCED AND SUBMIT THE THERMOSCAN FOR APPROVAL.

REFER TO THE POWER SCHEMATIC DRAWING FOR ADDITIONAL SWITCHBOARD REQUIREMENTS AND CONSTRUCTION NOTES. ENSURE ALL THREE PHASE CIRCUITS ARE PROVIDED WITH CORRECT PHASE ROTATION.

ENSURE ALL OUTLETS AND ISOLATORS ARE POSITIONED SUCH THAT THEY ARE NOT COVERED BY THE EQUIPMENT. THE FINAL POSITION OF ALL OUTLETS AND ISOLATORS ARE TO BE CONFIRMED ON SITE BY THE SCHOOLS REPRESENTATIVE.

REINSTATE THE EXISTING SOLAR PV PROTECTION SYSTEM INTO THE NEW MSB.

NOTES

6. LIGHTING

THE LIGHTING COMPONENT OF THE ELECTRICAL SERVICES SUB-CONTRACT INCLUDES ALL OF THE INTERNAL AND EXTERNAL LIGHT FITTINGS, LAMPS AND ACCESSORIES. PROVIDE ALL NECESSARY ACCESSORIES TO FACILITATE THE COMPLETE LIGHTING INSTALLATION. THE LIGHTING COMPONENT OF THE ELECTRICAL SERVICES SUB-CONTRACT INCLUDES THOUGH IT IS NOT LIMITED TO THE FOLLOWING EXTENT OF WORK:

- INTERNAL AND EXTERNAL LIGHTING.
- EMERGENCY AND EXIT LIGHTING.
- EARTHING OF THE LIGHTING INSTALLATION.
- LIGHTING CONTROL.
- LIGHTING SUBCIRCUITS.
- TESTING AND COMMISSIONING.

PROVIDE A SINGLE POINT EMERGENCY LIGHTING SYSTEM THAT COMPLIES WITH THE LATEST ISSUE OF ALL PARTS AS2293 AND THE RELEVANT PARTS OF THE NCC BCA. INSTALL EMERGENCY LIGHT FITTINGS NOMINATED AS MAINTAINED WITH THE LAMP PERMANENTLY ON SUPPLIED VIA AN UNSWITCHED ACTIVE MAINS SUPPLY WHEN THE MAINS SUPPLY IS AVAILABLE. WHEN THE MAINS SUPPLY IS NOT AVAILABLE, THE LAMP IS TO REMAIN ON SUPPLIED BY THE EMERGENCY PACK. SINGLE LAMP MAINTAINED EMERGENCY LIGHTS ARE NOT SWITCHED WITH THE LOCAL GENERAL AREA LIGHTING. (THE LAMP IS ALWAYS ON.)

INSTALL EMERGENCY LIGHT FITTINGS NOMINATED AS NON-MAINTAINED AS FOLLOWS:

- IF THE FITTING IS NOT BEING SWITCHED, THE LAMP IS TO REMAIN OFF WHEN THE MAINS SUPPLY IS AVAILABLE. WHEN THE MAINS SUPPLY IS NOT AVAILABLE THE LAMP IS TO BE SWITCHED ON SUPPLIED BY THE EMERGENCY PACK. UNSWITCHED SINGLE LAMP NON-MAINTAINED EMERGENCY LIGHTS ARE NOT SWITCHED WITH THE LOCAL GENERAL AREA LIGHTING. (THE LAMP IS ON ONLY WHEN THE MAINS SUPPLY IS NOT AVAILABLE.)
- IF THE FITTING IS BEING SWITCHED, THE LAMP IS TO BE SUPPLIED AND CONTROLLED WITH THE LOCAL GENERAL AREA LIGHTING WHEN THE MAINS SUPPLY IS AVAILABLE. WHEN THE MAINS SUPPLY IS NOT AVAILABLE THE LAMP IS TO BE SWITCHED ON, SUPPLIED BY THE EMERGENCY PACK. (THE LAMP IS ON WHEN TURNED ON WITH THE LOCAL GENERAL LIGHTING OR THE MAIN SUPPLY IS NOT AVAILABLE.)

7.0 COMMUNICATIONS CABLING

THE COMMUNICATIONS CABLING COMPONENT OF THIS CONTRACT INCLUDES NEW COMMUNICATION CAT 6 RJ45 OUTLETS CABLED TO MODULAR PATCH PANELS IN THE EXISTING COMMUNICATIONS RACK CR-LP VIA CAT 6 UTP CABLING.

PROVIDE THE STRUCTURED CABLING SOLUTION TO MATCH THE EXISTING USED ACROSS THE SITE AND PROVIDED IT WITH A MANUFACTURERS 15 YEAR WARRANTY.

THE COMMUNICATIONS CABLING COMPONENT OF THIS CONTRACT INCLUDES, BUT IS NOT LIMITED TO THE FOLLOWING EXTENT OF WORK:

- CAT 6 COMMUNICATIONS OUTLETS.
- CAT 6 CABLING.
- MODIFICATIONS TO COMMUNICATIONS RACK CR-LP TO ACCOMMODATE THE NEW PATCH PANELS.
- PATCH PANELS.
- FACTORY TERMINATED HDMI CABLES.
- LABELLING.
- TESTING AND COMMISSIONING.

ALL COMMUNICATIONS CABLING IS TO BE UNDERTAKEN BY AN ACMA LICENCE HOLDER. THE PATCH LEADS, FLY LEADS, POE SWITCH AND UPS WILL BE PROVIDED BY THE SCHOOL.

8. ABBREVIATIONS

- A - AMP CURRENT RATING
- AB - MOUNT ABOVE BENCH.
- AFFL - ABOVE FINISHED FLOOR LEVEL.
- BB - MOUNT BELOW BENCH.
- BH - MOUNT ON BULKHEAD.
- CEIL - MOUNT ON CEILING.
- CS - MOUNT WITHIN CEILING SPACE.
- C/W - COMPLETE WITH.
- DR - DRYER.
- DW - DISHWASHER.
- MCB - MINIATURE CIRCUIT BREAKER.
- MCCB - MOLDED CASE CIRCUIT BREAKER.
- MDB - MAIN DISTRIBUTION BOARD.
- MEN - MULTIPLE EARTH NEUTRAL LINK.
- MSB - MAIN SWITCHBOARD.
- MSSB - MECHANICAL SERVICES SWITCHBOARD.
- MW - MICROWAVE.
- N - NEON / LED INDICATOR WHEN ON.
- NTS - NOT TO SCALE.
- OV - OVEN.
- RCBO - CIRCUIT PROTECTED VIA A 30ma RESIDUAL CURRENT DEVICE INTEGRAL TO THE CIRCUIT BREAKER.
- REF - REFRIGERATOR.
- UNO - UNLESS NOTED OTHERWISE.
- WM - WASHING MACHINE.
- WP - WEATHERPROOF TO IP56 UNO.
- 500 - NUMBER DENOTES MOUNTING HEIGHT AFFL.

ELECTRICAL DESIGN GROUP BRISBANE PTY LTD ACN 092 710 793		THE COPYRIGHT OF THIS DRAWING REMAINS THE PROPERTY OF THE ELECTRICAL DESIGN GROUP.		PROJECT: KINGS CHRISTIAN COLLEGE - REEDY CREEK GLAs & STUDENT SERVICES KCC49		E CONSTRUCTION 03/06/2025	
TRADING AS: ELECTRICAL DESIGN GROUP		USE FIGURED DIMENSIONS IN PREFERENCE TO SCALE.		DRAWING: ELECTRICAL SERVICES NOTES		REV: DESCRIPTION: DATE:	
ALL DIMENSIONS TO BE VERIFIED ONSITE.		PROJECT NO: C2717a		DRAWING NO: E02		REVISION: E	
SCALE: NOT TO SCALE AT A1		68 GEMVALE ROAD, REEDY CREEK, QUEENSLAND					



ELECTRICAL DESIGN GROUP
ELECTRICAL BUILDING SERVICES CONSULTANTS
BRISBANE GOLD COAST

P.O.Box 15, Sherwood Q.4075
Phone: (07) 3278 4375
Email: brisbane@edg.net.au
Web: www.edg.net.au